วิธีการตั้งค่า D-Link รุ่น DIR-825 เป็นโหมด Access Point

รูปแบบการเชื่อมต่อ



1. เชื่อมต่อสายแลนที่ช่อง WAN ของ D-Link DIR-825 กับ ช่อง LAN ของ ONT ZTE F620 จากนั้นเชื่อมต่อ สายแลนที่ช่อง LAN ของ D-Link DIR-825 กับ LAN ของคอมพิวเตอร์ แล้วเปิด Browser ไปที่ http://192.168.0.1 เพื่อเข้าไปตั้งค่า

| 192.168.0.1/cgi-bin/webpre | oc | | 7 | ☆ 🔎 |
|----------------------------|--|-----------------------|--------------------|--------|
| Product Page : DIR-825 | | Hardware Version : G1 | Firmware Version : | 7.01TO |
| D-Link | | | | |
| | LOG IN Log in to the router : UserName : admin Password : Enter the correct password above and then type the characters you see in the nistre helow: | | | |
| | H T M 0 T Regenerate | | | |
| WIRELESS | | | | |

2.คลิ้กที่ WIRELESS 2.4G ที่ Wireless Mode เลือก Access Point กำหนดค่า SSID และ Security เสร็จ แล้วกด SAVE เพื่อบันทึกค่า จะมีข้อความขึ้นมาเตือนให้กด **ตกลง** แล้วรอ DIR-825 รีบูต เป็นอันเสร็จสิ้นเป็น การตั้งค่า

| DIR-825 | SETUP | WIRELESS 2.4G | WIRELESS 5.8G | TOOL | STATUS | HELP | | |
|----------|--|------------------------|------------------|----------------|--------|------|--|--|
| Basic | | | | | | | | |
| Security | Wireless | Racic Settings | 1 | | | | | |
| ACL | This sees is used to see from the second to window 140 like window second in | | | | | | | |
| Advanced | I his page is used to configure the parameters for the wireless LAN like wireless encryption settings, channel and band. | | | | | | | |
| WPS | Wireless Mode : Access Point Access Point : Access Point | | | | | | | |
| | | | | | | | | |
| | Count | ry: USA | v v | | | | | |
| | Chann | el : Auto Sca | n(recommended) 🔻 | Current Channe | l: 3 | | | |
| | Wireless | Mode : 802.11g | +n ▼ | | | | | |
| | SSID Isol | ation : Off v | | | | | | |
| | 11n Setti | 11n Settings | | | | | | |
| | Channel Wi | Channel Width 20/40M V | | | | | | |
| | SSID Settings | | | | | | | |
| | SSID index : | 1 🔻 | | | | | | |
| | SSID : | TOT fiber 2U- | 2G_06A8 | | | | | |
| | Visibility St | • Visible | Invisible | | | | | |
| | Max User In : | odex 0 | | | | | | |
| | User Isolati | ion: Off • | 3 | | | | | |
| | Save | | | | | | | |

| DIR-825 | ระบบค พบ 192.168.0.1 บอกว่า: × | |
|-----------------|---|--|
| Basic | If you change the mode, the device is going to reboot. Do you want to continue? | |
| Security ACL | Wireless Basi uniin | |
| Advanced | This page is used ryption | |
| WPS | Wireless Mode : Access Point | |
| Repeater | Access Point : | |
| | Country : USA 🔻 | |
| | Channel : Auto Scan(recommended) Current Channel : 1 | |
| | Wireless Mode : 802.11g+n T | |
| | SSID Isolation : Off • | |
| | Channel Width 20/40M V | |
| | SSID Settings | |
| | SSID index 1 • | |
| | SSID: TOT fiber 2U-2G_06A8 | |
| | Visibility Status : • Visible • Invisible | |
| | Max User Index : | |
| | User Isolation : Off 🔻 | |
| | Save Cancel | |